

Advanced Micro Ring Resonator Filter Technology

G. Lenz and C. K. Madsen Lucent Technologies, Bell Labs


maintaining the data needed, and c including suggestions for reducing	election of information is estimated to completing and reviewing the collect this burden, to Washington Headqu uld be aware that notwithstanding ar OMB control number.	ion of information. Send comments arters Services, Directorate for Information	regarding this burden estimate mation Operations and Reports	or any other aspect of the property of the contract of the con	nis collection of information, Highway, Suite 1204, Arlington	
1. REPORT DATE 18 APR 2000		2. REPORT TYPE N/A		3. DATES COVERED		
4. TITLE AND SUBTITLE	5a. CONTRACT NUMBER					
Advanced Micro Ring Resonator Filter Technology				5b. GRANT NUMBER		
				5c. PROGRAM ELEMENT NUMBER		
6. AUTHOR(S)				5d. PROJECT NUMBER		
				5e. TASK NUMBER		
				5f. WORK UNIT NUMBER		
7. PERFORMING ORGANIZATION NAME(S) AND ADDRESS(ES) Lucent Technologies				8. PERFORMING ORGANIZATION REPORT NUMBER		
9. SPONSORING/MONITORING AGENCY NAME(S) AND ADDRESS(ES)				10. SPONSOR/MONITOR'S ACRONYM(S)		
				11. SPONSOR/MONITOR'S REPORT NUMBER(S)		
12. DISTRIBUTION/AVAIL Approved for publ	LABILITY STATEMENT ic release, distributi	on unlimited				
	OTES OM for Military Pla contains color imag	-	eld in McLean, V	A on April 1	8-19, 2000, The	
14. ABSTRACT						
15. SUBJECT TERMS						
16. SECURITY CLASSIFIC	17. LIMITATION OF ABSTRACT	18. NUMBER OF PAGES	19a. NAME OF			
a. REPORT unclassified	b. ABSTRACT unclassified	c. THIS PAGE unclassified	UU	19	RESPONSIBLE PERSON	

Report Documentation Page

Form Approved OMB No. 0704-0188



All-Pass Filters





Mathematical Form

$$H(\omega) = \prod_{n=0}^{N-1} \frac{e^{j\omega} - z_n}{e^{j\omega} z_n^* - 1} = \prod_{n=0}^{N-1} \frac{e^{j\omega} - r_n e^{j\theta_n}}{e^{j\omega} r_n e^{-j\theta_n} - 1}$$

$$|H(\omega)| = 1$$


$$|H(\omega)| = 1$$
 $\phi(\omega) = \sum_{n=0}^{N-1} Arg \left[\frac{e^{j\omega} - z_n}{e^{j\omega} z_n^* - 1} \right]$



Phase equalization without amplitude distortion



Group Delay




Larger FSR \Rightarrow smaller dispersion; More stages \Rightarrow more dispersion




Four-Stage All-Pass Filter

Approximation of Linear group delay across pass band




Equi-ripple design





Four-Stage All-Pass Filter Experimental






Dispersion vs. Bandwidth Tradeoff

25 GHz Channel Spacing


100 GHz Channel Spacing



APPROVED FOR PUBLIC RELEASE, DISTRIBUTION UNLIMITED




All-Pass Filter - Effect of Finite Loss







Broadband All-Pass Filters

Basic Design






Achieving required coupling κ practically not feasible






Multi-channel Dispersion Compensation



Constant dispersion compensation




Dispersion slope compensation




Thin-film All-Pass Filter

Single-stage Silica substrate (25 GHz FSR)




Package loss 0.3 dB



Gires-Tournois
Interferometer (GTI)



General Construction of an All-Pass Filter



This is an all-pass filter if:

1.
$$\det(M) = 1$$


1.
$$det(M) = 1$$

2. $M_{22} = M_{11}^*$

FSR determined by feedback path delay



More General All-Pass Structures




APPROVED FOR PUBLIC RELEASE, DISTRIBUTION UNLIMITED


REVIEW OF THIS MATERIAL DOES NOT IMPLY DEPARTMENT OF DEFENSE INDORSEMENT OF FACTUAL ACCURACY OR OPINION



Simple Case




Scaling problem:



Larger FSR \Rightarrow Smaller rings \Rightarrow Larger bend loss \Rightarrow Larger Δ material \Rightarrow Coupler gap too small



MZI-based APF




This design is <u>no longer sensitive</u> to the couplers

Equivalent to simple case, but with tunable coupling



Another solution





Vertical grating-assisted coupling





Nonlinear all-pass filters





(Heebner and Boyd, Opt. Lett., 1999)

$$\Phi_{eff} \sim \left(\frac{2\pi}{\lambda} n_2 IL\right) 4F^2$$

$$F \sim \frac{\tau_{\text{max}}}{T}$$


However, large F implies small bandwidth



For ~1 ps timescales requires very small rings or disks (~1 μm)



Practical considerations



Vertical coupling



 $R \sim 1 \ \mu m$ $F \sim 30$ Cavity losses?



Summary

- Ring resonators can be used as tunable optical phase equalizers
- Large bandwidth devices require many small rings
- Ring loss needs to be minimized
- Nonlinear micro rings may be used for fast all-optical switching